


# FRAMELESS BRUSHLESS DC (BLDC) MOTORS

## Introduction

BEI Kimco's frameless motor part set design allows for the motor to be fully integrated within the customer assembly resulting in the highest ratio of torque to volume. In this configuration the motor's rotor and stator are housed within the customer's "next higher" assembly utilizing a common shaft and bearing system. This results in increased coupling efficiencies, reduced system size, weight and cost.

The high magnetic pole count pancake "Torquer" motor produces exceptionally low cogging for smooth low speed operation and high accuracy positioning applications.



## Features

- Highest energy product permanent magnet rotor design for improved efficiency
- High pole count rotor for smooth operation
- Proprietary magnetic circuit design for optimal efficiency
- Low torque ripple
- Encapsulated Stator assemblies for improved thermal performance

## FRAMELESS BRUSHLESS DC (BLDC) MOTOR CONFIGURATIONS

Part Number	Peak Torque (N-m / oz-in)	Continuous Stall Torque (N-m / oz-in)	Motor Constant (N-m/√watts)/(oz-in/√watts)	Weight (g/ oz)
DIP11-11-001A	0.011/6	0.03/4.58	0.014/1.97	51/1.8
DIP20-06-HPZ	0.099/14	0.029/4.2	0.012/1.7	59.5/2.1
DIP20-09-HPZ	0.3/43	0.06/9.5	0.023/3.23	127.5/4.5
DIP16-08-008A	0.14/20	0.1/14.7	0.032/4.61	68/2.4
DIP13-12-012A	0.16/22.8	0.05/7.4	0.01/2	70.9/2.5
DIP13-12-004A	0.17/24	0.05/7.5	0.01/2	70.9/2.5
DIP20-19-HPZ	0.66/93	0.15/22	0.04/5	283.5/10
DIP30-07-001A	0.71/100	0.095/13.5	0.095/13.5	212.6/7.5
DIP24-11-001A	0.85/120	0.33/46	0.077/10.5	263.6/9.3
DIP37-12-024Z	1.13/160	0.35/50	0.063/8.92	1134/40
DIP21-22-002A	1.76/250	0.38/54	0.095/13.5	436.5
DIP38-18-001A	3.5/496	2.68/380	0.35/50	1134/40
DIP38-22-001A	9.18	3.05/423	0.385/54.6	2098/74

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at [www.sensata.com](http://www.sensata.com) SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

## CONTACT US

### Americas

+1 (760) 597 7042

[sales.beikimco@sensata.com](mailto:sales.beikimco@sensata.com)

### Europe, Middle East & Africa

+1 (760) 597 7042

[support@sensata.com](mailto:support@sensata.com)

### Asia Pacific

[sales.isasia@list.sensata.com](mailto:sales.isasia@list.sensata.com)

China +86 (21) 2306 1500

Japan +81 (45) 277 7117

Korea +82 (31) 601 2004

India +91 (80) 67920890

Rest of Asia +603-5566 6001